— M2M Data Mobile App User Guide —

- Change Password -



— Search SIMs —







— Activate a SIM (2 option) —

1. Select a SIM card by clicking on it;		ę	d 🛔 9:40	
2. In the menu that opens, select the item Sim status ; —	F SIM Lis		<	
3. Click on the State field ;	Seurch t	<	SIM Status	
4. Select Activate or Activate to TestProductive and press the back arrow. Activation will happen automatically.		204576651273	IMSE ICCID: 893 MSISDN: State State	204543349870000 314403900108712678 2045435871111 Productive
		Send Command	окв 2024- 06:2	< State Select Action
		Connectivity	Customer M2M Data	Activate
		Activation	→ ● Select Action	Activate to TestProductive
			M2M Data / Opti	Suspend
		Location	SHOW LO	Resume
		0	al SE E	Terminate
		Transfer SIM	Data Usage	at 🖾 🛍 🕅
		at 10 E	a 8	

- Suspend and Terminate a SIM (1 option) -



— Suspend and Terminate a SIM (2 option) —

1. Select a SIM card by clicking on it;		Ş	9:40	⊜⊿ 1 9:40
2. In the menu that opens, select the item Sim status ; ——	SIM List		<	
3. Click on the State field ;	Seirch t	<	SIM Status	
4. Select Terminate or Suspend . Change will happen automatically.		204576651273	IMSI: ICCID: 893 MSISDN: State: State:	204543349870000 814403000108712678 204543349871111 Productive
		Send Command	С 0 КВ 2024- 06:2	< State Select Action
		Connectivity	Customer M2M Data	Activate
		Activation	CSP M2M Date / Opti	Activate to TestProductive Suspend
		Location	SHOW LO	C Resume
		8	al SE E	Terminate
		Transfer SIM	Data Usage	at 10 III At 8
		at 🔯 🖾	# 8	

— Send Custom Command —

1. Select a SIM card by clicking on it;

2. In the menu that opens, select the item **Send Commands**;

3. Click on the **Select command** field;

4. Select **Custom command** and press the Select button;

5. You will have a **Field** for manually entering a command.

< 2045766512738691 € 1 9:40 < 0 Commands ₹ 1 9:40 SIM Statu < Ð 423946278946825 Select Command 1 € 1 9:40 Send Command IMSI 763879458235427 < Commands Custom command CSP M2M Data / Optim @ ICCID 423946278946829364 Connectivity Command name 1 Command Select command IMSI 7538794582354278 0 Command name 2 Activation CSP M2M Data / Optimus Profile 0 Command Custom Command > 說 at. 13 Location Enter Command #WHERE at. 8 Transfer SIM Data Usage SEND 12 調 11 3 額 123 24 100 -1 al.

— Send Template Command —

1. Select a SIM card by clicking on it;

2. In the menu that opens, select the item **Send Commands**;

- 3. Click on the **Select command** field;
- 4. Select **Command** and press the Select button;
- 5. Click the Send button.







— Transfer SIM —

